

KombiSIGN 71 / Permanent Beacon 641

Perm. light element 12-230VAC/DC CL



| | |
|-----------|--------------|
| Part No.: | 641.400.00 |
| Series: | KombiSIGN 71 |



MECHANICAL DATA

| | |
|-----------------------------|-------------|
| Height | 66 mm |
| Diameter | 70 mm |
| Materials | PC |
| Dome colour | Clear |
| Protection category | IP65 |
| Tension relief | Not present |
| Working temperature minimum | -20°C |
| Working temperature maximum | +50°C |
| Weight with packaging | 71 g |
| Product weight | 56 g |

ELECTRICAL DATA

| | |
|------------------------|--------------------------|
| Operating voltage | 12-230V |
| Operating voltage type | AC/DC |
| Protection class | Protection class 2 |
| Pollution degree | 3 |
| Overvoltage category | II |
| Isolation voltage | Ui = 250V; Uimp = 2.500V |
| Power illuminant | max.5W |

OPTICAL DATA

| | |
|----------------------|-----------------|
| Light source | Filament lamp |
| Light colour | White |
| Optical signal image | Permanent |
| Service life optical | depends on bulb |
| Lamp fitting/socket | B15d |

APPROVAL DATA

| | |
|-------------------------------|-----------------------|
| Conforms with CE | Yes |
| Conforms with RoHS directive | Yes |
| WEEE | Yes |
| Conforms with ATEX-directive | No |
| Conforms with CCC | No |
| Conforms with UL | cULus |
| UL Type Rating | Type 12 |
| Conforms with FCC | No |
| Conforms with IC | No |
| EAC certificate available | Yes |
| Conforms with UKCA (Importer) | Yes (WERMA (UK) Ltd.) |



For additional installation and mounting information, refer to the appropriate user guide at www.werma.com. This printed copy is for information only and is subject to alteration.

KombiSIGN 71 / Permanent Beacon 641

Perm. light element 12-230VAC/DC CL

| | |
|-----------------------|----|
| Conforms with CMIM | No |
| Conforms with AS-I | No |
| ICAO Certification | No |
| Conforms with DNV | No |
| Conforms with RoHS CN | No |
| Conforms with VdS | No |

DRAWING



For additional installation and mounting information, refer to the appropriate user guide at www.werma.com. This printed copy is for information only and is subject to alteration.